



Phil 30D

Cod.62051D

Notch filter against noises at cabinet level, with toroidal coil, used on the power line communication.

PHIL 30D reduce the effects coming from an outdoor power supply network, which could cause malfunctions to an installation. The filter can be used even to avoid that the Power-line signal transmitted between ANDROS and SYRA spreads out in not proper areas and that any capacitive charge connected in the installation cause a diminishing of the signal itself.

Technical specifications

Working voltage
230 V~ +/- 10%

Power dissipated

0,22W @ 10A
0,95W @ 20A
2,22W @ 30A

Charge max. Current
30 A

Protection degree
IP20

Dimensions
34,6 x 89 x 65 mm (2 DIN modules)

Weight
260 gr

© Umpi Elettronica Srl. All rights reserved.

Specifications are subjected to change without notice.

www.umpi.it www.minos-system.com



Via Respighi15, 47841 Cattolica (RN)
T: +39 0541833160 F: +39 0541833161